





## Proper Grounding Tips

**Proper Grounding:** Proper grounding is critical for the correct operation of your Speartech engine control system. Failure to properly ground the system can result in anything from a no start condition, to erratic operation, to ECM/wiring harness damage. Vehicles vary in how they are grounded but you must ensure the negative battery cable, engine block, chassis/frame of vehicle, and wiring harness are all properly connected together at the ground level. Do NOT connect any ground cables to the rocker covers as these are usually isolated on LS/LT engines. The engine block and/or cylinder heads are the best places to attach ground connections. Make sure all connections are clean and tight. We have seen instances of improperly grounded systems that have resulted in all ground current going through the wiring harness and ECM, damaging both parts beyond repair. Failures like this are NOT covered under warranty!